

WiFi / Bluetooth Jammer WLJ100

The new WiFi jammer has been designed to cut-off wireless LAN networks in a radius of 20 meters.

This device transmits white noise signal in WiFi frequencies, 2400-2483 MHz

and cuts-off all Wireless network.

Even the Bluetooth communication will be cut off when WLJ100 takes action.

This unit helps to prevent from unauthorized person to "leak" out confidential information.



Technical Specifications

<i>RF Characteristics</i>	
Output Power	500mw
Internal Modulation	FM Hopping frequency
Signal Source	PLL synthesized
Power Supply	12VDC
Modules Per Unit	1
Remote Control	Infrared (Option)
Antennas	External Omni-Directional
<i>Jamming Frequency Bands</i>	
Frequency Bands	2400-2483 MHz
Air Interface Standards	WiFi, Bluetooth
<i>Physical Data</i>	
Dimensions	120 x 60 x 25 mm
Weight (w/o batteries)	Approx. 0.3Kg
<i>Environment Of Operation</i>	
Operating Temp.	-10°C - 60°C
Humidity	5% - 80%
<i>Optional Accessories</i>	
Rechargeable Battery	1.5 AH
Universal Power Supply	90-260VAC

PHANTOM TECHNOLOGIES LTD.

68 AMAL ST., PETAH-TIKVA, ISRAEL

TEL. +972-3-9215720 FAX. +972-3-9215434

Web-Site: www.phantom.co.il